

三相接触器							
JQ-79F		50×50×61 ≤285g	3H	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	15A, 60Vd. c. 15A, 115/200Va. c. 10A, 380Va. c.	196
JQ-36F		107×62×100 ≤700g	3H3D	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	50A, 60Vd. c. 50A, 115/200Va. c. 25A, 380Va. c.	198
JQ-36FH		107×62×95 ≤650g	3H	-55~85	正弦: 98m/s <sup>2</sup> 5~500Hz	50A, 60Vd. c. 50A, 115/200Va. c. 25A, 380Va. c.	200
JQ-28F		117×66×113 ≤1250g	3H3D	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	100A, 115/200Va. c. 50A, 380Va. c.	202
JQ-28FH		117×66×95 ≤1100g	3H	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	100A, 115/200Va. c. 50A, 380Va. c.	204
JQ-37F		117×66×113 ≤1300g	3H3D	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	150A, 60Vd. c. 150A, 380Va. c.	206
JQ-37FH		117×66×95 ≤1200g	3H	-55~85	正弦: 98m/s <sup>2</sup> 10~500Hz	150A, 60Vd. c. 150A, 380Va. c.	208

产品型号	产品照片	外形尺寸(mm) 及重量	触点 型式	环境温度 (°C)	振 动	触点负载	页码
JQ-45F		76.4×80×64.5 450g±10%	3H	-55~85	正弦: 98m/s <sup>2</sup> 5~2000Hz 随机: 0.035g <sup>2</sup> /Hz	主: 30A, 115/200Va. c. 30A, 220/380Va. c. 辅: 5A, 28Vd. c.	210
JQ-46F		90×97×76 710g±10%		-55~85	正弦: 98m/s <sup>2</sup> 5~2000Hz 随机: 0.035g <sup>2</sup> /Hz	主: 60A, 115/200Va. c. 60A, 220/380Va. c. 辅: 5A, 28Vd. c.	212
JQ-47F		102.2×104×86 970g±10%		-55~85	正弦: 98m/s <sup>2</sup> 5~2000Hz 随机: 0.035g <sup>2</sup> /Hz	主: 120A, 115/200Va. c. 120A, 220/380Va. c. 辅: 5A, 28Vd. c.	214
JQ-38F		124×102×92 ≤1600g		-55~85	正弦: 98m/s <sup>2</sup> 5~2000Hz 随机: 0.035g <sup>2</sup> /Hz	主: 200A, 115/200Va. c. 200A, 220/380Va. c. 辅: 5A, 28Vd. c.	216
JQ-QY47F		181×139×141 ≤5kg		-55~85	正弦: 98 m/s <sup>2</sup> 5~500Hz	主: 250A, 380Va. c. 250A, 660Va. c. 250A, 1140Va. c. 250A, 1500Va. c. 辅: 10A, 380Va. c.	218
JCQ-3H400F		240×220×165 ≤11.5kg		-55~85	正弦: 98 m/s <sup>2</sup> 10~500Hz	主: 400A, 3600Va. c. 辅: 5A, 110Vd. c.	221
JCQ-3H500F		194×178×151 ≤8kg		-55~85	正弦: 98 m/s <sup>2</sup> 10~500Hz	主: 500A, 380Va. c. 500A, 660Va. c. 500A, 1140Va. c. 500A, 1500Va. c. 辅: 5A, 220Va. c.	224
JQ-45FH		90×80×64.5 550g±10%		4H	-55~85	正弦: 98m/s <sup>2</sup> 10~2000Hz	主: 40A, 115/200Va. c. 40A, 220/380Va. c. 辅: 5A, 28Vd. c.
JQ-46FH		107×97×76 900g±10%	-55~85		正弦: 98m/s <sup>2</sup> 10~2000Hz	主: 80A, 115/200Va. c. 80A, 220/380Va. c. 辅: 5A, 28Vd. c.	229
JQ-47FH		122.2×104×86 1250g±10%	-55~85		正弦: 98m/s <sup>2</sup> 10~500Hz	主: 125A, 115/200Va. c. 125A, 220/380Va. c. 辅: 5A, 28Vd. c.	231

产品型号	产品照片	外形尺寸(mm) 及重量	触点 型式	环境温度 (°C)	振 动	触点负载	页码
<b>三相密封接触器</b>							
JCQ-3H120M		87.5×87.5×85 ≤910g	3H	-55~85	随机振动: 0.084 g <sup>2</sup> /Hz, 20~2000 Hz	主: 120A, 115Va. c. 电机: 80A, 115Va. c. 辅: 5A, 28Vd. c.	233
JCQ-3Z60M		61×61×79 ≤460g	3Z	-55~85	随机振动: 0.084 g <sup>2</sup> /Hz, 10~2000 Hz	主: 60A, 115Va. c. 电机: 40A, 115Va. c. 辅: 5A, 28Vd. c.	235
JCQ-3Z90M		91×86×86.4 ≤820g		-55~85	随机振动: 0.05 g <sup>2</sup> /Hz, 5~2000 Hz	主: 90A, 115Va. c. 电机: 80A, 115Va. c. 辅: 5A, 28Vd. c.	237
JCQ-3Z120M		87.5×87.5×104 ≤1030g		-55~85	随机振动: 0.084 g <sup>2</sup> /Hz, 20~2000 Hz	主: 120A, 115Va. c. 电机: 80A, 115Va. c. 辅: 5A, 28Vd. c.	239
JQ-50M		118.5×91.5×104 ≤1200g		-55~85	随机振动: 0.084 g <sup>2</sup> /Hz, 20~2000 Hz	主: 175A, 115Va. c. 电机: 80A, 115Va. c. 辅: 5A, 28Vd. c.	241